## **KBVISION**

## KX-DAi8216H3

16 Channel Penta-brid 5M-N/1080P 1U 2HDDs DVR

Design and specifications are subject to change without notice. Pictures in the document are for reference only, and the actual product shall prevail.



- $\cdot$  H.265+/H.265 dual-stream video compression
- $\cdot$  Supports Full-channel AI Coding
- · Supports HDCVI/AHD/TVI/CVBS/IP video inputs
- $\cdot$  Max 24 channels IP camera inputs, each channel up to 6MP; Max 128 Mbps incoming bandwidth
- $\cdot$  Up to 2 channels video stream (analog channel) Perimeter Protection
- $\cdot$  Up to 16 channels video stream (analog channel) SMD Plus
- $\cdot$  Up to 2 channels video stream (analog channel) human face recognition
- · IoT & POS functionalities



System		Dual-stream	Supported (D1/CIF (1 fps-15 fps)).
Main Processor	Embedded processor	Video Frame Rate	PAL: 1 fps-25 fps.
Operating System	Embedded Linux		NTSC: 1 fps–30 fps.
Perimeter Protection		Video Bit Rate	32 Kbps–6144 Kbps Per Channel
Perimeter Performance AI by Recorder (Number of Channels)		Audio Sampling	8 KHz, 16 bit Per Channel
		Audio Bit Rate	64 Kbps Per Channel
Face Detection		Bit Rate Type	Video stream and composite stream.
Face Attributes Face Detection Performance of Al by	6 attributes: Gender, age groups (6), glasses, expressions (8), face mask, beard, with up to four detection panels displayed at the same time. 2 channels, and a single channel can detect up to 12	Video Output	1 HDMI, 1 VGA VGA: 1920 × 1080, 1280 × 1024, 1280 × 720 HDMI: 3840 × 2160, 1920 × 1080, 1280 × 1024, 1280 × 720 It changes to 1920 × 1080, 1280 × 1024, 1280 × 720 when Face or IVS&SMD is selected in AI Mode.
Recorder (Number of Channels)	faces.	Multi-screen Display	When IP extension mode not enabled: 1/4/8/9/16 When IP extension mode enabled: 1/4/8/9/16/25
Face Recognition	Up to 10 face databases and 10,000 pictures.	Third-party Camera Access	Onvif, RTSP, Panasonic, Sony, Axis, Arecont, Pelco, Canon, Samsung
. ,	2 channels	Compression Standard	
Face Recognition Performance of AI by		Video Compression	AI Coding/H.265+/H.265/H.264+/H.264
Recorder (Number of Channels)		Audio Compression	G.711A/G.711u/PCM
SMD Plus		Network	
SMD Plus by Recorder	Full-channel SMD Plus (AI by recorder), secondary filtering for human and motor vehicle SMD Plus, reducing false alarms caused by leaves, rain and lighting condition change	Network Protocol	HTTP, HTTPS, TCP / IP, IPv4, RTSP, UDP, SMTP, NTP, DHCP, DNS, DDNS, P2P
		Mobile Phone Access	iPhone, iPad, Android
		Interoperability	ONVIF 16.12, CGI Conformant
Audio and Video		Browser	Chrome, IE9 or above, Firefox
Analog Camera Input	16 channels, BNC: adaptive access by default; HDCVI, AHD, TVI and CVBS access can be configured.	Network Mode	Single-address mode
Camera Input	1. CVI: 5MP, 4MP, 1080p@25/30 fps, 720p@50/60 fps, 720p@25/30 fps. 2. TVI: 5MP, 4MP, 3MP, 1080p@25/30, 720p@25/30 fps.	Recording Playback	
		Record Mode	Manual, Schedule (General, Continuous), MD (Video detection: Motion Detection, Video Loss, Tampering), Alarm, Stop
IP Camera Input	3. AHD: 5MP, 4MP, 3MP, 1080p@25/30, 720p@25/30 fps. 16+8 channels, each channel up to 6MP	Recording Playback	1/4/9/16 It changes to 1/4/9 split when Face or IVS&SMD is selected in AI Mode.
Encoding Capacity	All channel 5M-N (1 fps–10 fps); 4M-N/1080p (1 fps–15 fps); 1080N/720p/960H/D1/CIF (1 fps–25/30 fps)	Backup Method	USB Device/Network

# **KB**VISION

## KX-DAi8216H3

#### 16 Channel Penta-brid 5M-N/1080P 1U 2HDDs DVR

Design and specifications are subject to change without notice. Pictures in the document are for reference only, and the actual product shall prevail.

Playback ModeInstant playback, general playback, creat playback, deg playback, smart playback, face and motion detection)StorageDisk GroupYesAlarmMotion detection, Video Loss, tampering, and local alarmGeneral AlarmNo disk, disk error, low space, offline, ip conflict, MAC conflictAnomaly AlarmNo disk, disk error, low space, offline, ip conflict, MAC conflictIntelligent AlarmFace detection, face recognition, perimeter protectionAlarm LinkageRecord, snapshot (panoramic), IPC external alarm output, access controller, voice prompt, buzzer, log, preset, emailPortsIntelligent AlarmAudio Input1, RCA (external) 16, BNC (coaxial)Audio Output1, RCATwo-way TalkYes (share the same audio input with the first channel) 2 SATA Ports, up to 16TB for a single HDD, the maximum HDD capacity varies with environment temperatureRS-4851 Port, for PTZ ControlUSB2 USB Ports (1 USB 2.0, 1 USB 3.0)HDMI1VGA1Network Port1 (10/100/1000 Mbps Ethernet port, RJ-45)GeneralPower SupplyPower SupplyDC12V, 4A		Instant playback, general playback, event playback, tag			
Disk GroupYesAlarmMotion detection, Video Loss, tampering, and local alarmGeneral AlarmMotion detection, Video Loss, tampering, and local alarmAnomaly AlarmNo disk, disk error, low space, offline, ip conflict, MAC conflictIntelligent AlarmFace detection, face recognition, perimeter protectionAlarm LinkageRecord, snapshot (panoramic), IPC external alarm output, access controller, voice prompt, buzzer, log, preset, emailPortsAudio Input1, RCA (external) 16, BNC (coaxial)Audio Output1, RCATwo-way TalkYes (share the same audio input with the first channel)HDD Interface2 SATA Ports, up to 16TB for a single HDD, the maximum HDD capacity varies with environment temperatureRS-4851 Port, for PTZ ControlUSB2 USB Ports (1 USB 2.0, 1 USB 3.0)HDMI1VGA1Network Port1 (10/100/1000 Mbps Ethernet port, RI-45)General	Playback Mode				
AlarmGeneral AlarmMotion detection, Video Loss, tampering, and local alarmAnomaly AlarmNo disk, disk error, low space, offline, ip conflict, MAC conflictIntelligent AlarmFace detection, face recognition, perimeter protectionAlarm LinkageRecord, snapshot (panoramic), IPC external alarm output, access controller, voice prompt, buzzer, log, preset, emailPortsAudio Input1, RCA (external) 16, BNC (coaxial)Audio Output1, RCATwo-way TalkYes (share the same audio input with the first channel)HDD Interface2 SATA Ports, up to 16TB for a single HDD, the maximum HDD capacity varies with environment temperatureRS-4851 Port, for PTZ ControlUSB2 USB Ports (1 USB 2.0, 1 USB 3.0)HDMI1VGA1Network Port1 (10/100/1000 Mbps Ethernet port, RJ-45)GeneralEthernal	Storage				
General AlarmMotion detection, Video Loss, tampering, and local alarmAnomaly AlarmNo disk, disk error, low space, offline, ip conflict, MAC conflictIntelligent AlarmFace detection, face recognition, perimeter protectionAlarm LinkageRecord, snapshot (panoramic), IPC external alarm output, access controller, voice prompt, buzzer, log, preset, emailPortsAudio Input1, RCA (external) 16, BNC (coaxial)Audio Output1, RCATwo-way TalkYes (share the same audio input with the first channel)HDD Interface2 SATA Ports, up to 16TB for a single HDD, the maximum HDD capacity varies with environment temperatureRS-4851 Port, for PTZ ControlUSB2 USB Ports (1 USB 2.0, 1 USB 3.0)HDMI1VGA1Network Port1 (10/100/1000 Mbps Ethernet port, RJ-45)General	Disk Group	Yes			
General AlarmalarmAnomaly AlarmNo disk, disk error, low space, offline, ip conflict, MAC conflictIntelligent AlarmFace detection, face recognition, perimeter protectionAlarm LinkageRecord, snapshot (panoramic), IPC external alarm output, access controller, voice prompt, buzzer, log, preset, emailPorts1, RCA (external) 16, BNC (coaxial)Audio Input1, RCA (external) 16, BNC (coaxial)Audio Output1, RCATwo-way TalkYes (share the same audio input with the first channel)HDD Interface2 SATA Ports, up to 16TB for a single HDD, the maximum HDD capacity varies with environment temperatureRS-4851 Port, for PTZ ControlUSB2 USB Ports (1 USB 2.0, 1 USB 3.0)HDMI1VGA1Network Port1 (10/100/1000 Mbps Ethernet port, RJ-45)GeneralImage Interface	Alarm				
Anomaly AlarmconflictIntelligent AlarmFace detection, face recognition, perimeter protectionAlarm LinkageRecord, snapshot (panoramic), IPC external alarm output, access controller, voice prompt, buzzer, log, preset, emailPorts1, RCA (external) 16, BNC (coaxial)Audio Input1, RCA (external) 16, BNC (coaxial)Audio Output1, RCATwo-way TalkYes (share the same audio input with the first channel)HDD Interface2 SATA Ports, up to 16TB for a single HDD, the maximum HDD capacity varies with environment temperatureRS-4851 Port, for PTZ ControlUSB2 USB Ports (1 USB 2.0, 1 USB 3.0)HDMI1VGA1Network Port1 (10/100/1000 Mbps Ethernet port, RJ-45)	General Alarm				
Alarm LinkageRecord, snapshot (panoramic), IPC external alarm output, access controller, voice prompt, buzzer, log, preset, emailPortsAudio Input1, RCA (external) 16, BNC (coaxial)Audio Output1, RCA (external) 16, BNC (coaxial)Audio Output1, RCATwo-way TalkYes (share the same audio input with the first channel)HDD Interface2 SATA Ports, up to 16TB for a single HDD, the maximum HDD capacity varies with environment temperatureRS-4851 Port, for PTZ ControlUSB2 USB Ports (1 USB 2.0, 1 USB 3.0)HDMI1VGA1Network Port1 (10/100/1000 Mbps Ethernet port, RJ-45)General	Anomaly Alarm				
Alarm Linkageoutput, access controller, voice prompt, buzzer, log, preset, emailPortsAudio Input1, RCA (external) 16, BNC (coaxial)Audio Output1, RCATwo-way TalkYes (share the same audio input with the first channel)HDD Interface2 SATA Ports, up to 16TB for a single HDD, the maximum HDD capacity varies with environment temperatureRS-4851 Port, for PTZ ControlUSB2 USB Ports (1 USB 2.0, 1 USB 3.0)HDMI1VGA1 (10/100/1000 Mbps Ethernet port, RJ-45)GeneralInterface	Intelligent Alarm	Face detection, face recognition, perimeter protection			
Audio1, RCA (external) 16, BNC (coaxial)Audio Output1, RCAAudio Output1, RCATwo-way TalkYes (share the same audio input with the first channel)HDD Interface2 SATA Ports, up to 16TB for a single HDD, the maximum HDD capacity varies with environment temperatureRS-4851 Port, for PTZ ControlUSB2 USB Ports (1 USB 2.0, 1 USB 3.0)HDMI1VGA1Network Port1 (10/100/1000 Mbps Ethernet port, RJ-45)General	Alarm Linkage	output, access controller, voice prompt, buzzer, log,			
Audio Input16, BNC (coaxial)Audio Output1, RCATwo-way TalkYes (share the same audio input with the first channel)HDD Interface2 SATA Ports, up to 16TB for a single HDD, the maximum HDD capacity varies with environment temperatureRS-4851 Port, for PTZ ControlUSB2 USB Ports (1 USB 2.0, 1 USB 3.0)HDMI1VGA1Network Port1 (10/100/1000 Mbps Ethernet port, RJ-45)GeneralImage: Control Set	Ports				
Two-way TalkYes (share the same audio input with the first channel)HDD Interface2 SATA Ports, up to 16TB for a single HDD, the maximum HDD capacity varies with environment temperatureRS-4851 Port, for PTZ ControlUSB2 USB Ports (1 USB 2.0, 1 USB 3.0)HDMI1VGA1Network Port1 (10/100/1000 Mbps Ethernet port, RJ-45)General	Audio Input				
HDD Interface2 SATA Ports, up to 16TB for a single HDD, the maximum HDD capacity varies with environment temperatureRS-4851 Port, for PTZ ControlUSB2 USB Ports (1 USB 2.0, 1 USB 3.0)HDMI1VGA1Network Port1 (10/100/1000 Mbps Ethernet port, RJ-45)General	Audio Output	1, RCA			
HDD Interfacemaximum HDD capacity varies with environment temperatureRS-4851 Port, for PTZ ControlUSB2 USB Ports (1 USB 2.0, 1 USB 3.0)HDMI1VGA1Network Port1 (10/100/1000 Mbps Ethernet port, RJ-45)General	Two-way Talk	Yes (share the same audio input with the first channel)			
USB2 USB Ports (1 USB 2.0, 1 USB 3.0)HDMI1VGA1Network Port1 (10/100/1000 Mbps Ethernet port, RJ-45)General	HDD Interface	maximum HDD capacity varies with environment			
HDMI     1       VGA     1       Network Port     1 (10/100/ Mbps Ethernet port, RJ-45)       General	RS-485	1 Port, for PTZ Control			
VGA 1 Network Port 1 (10/100/1000 Mbps Ethernet port, RJ-45) General	USB	2 USB Ports (1 USB 2.0 , 1 USB 3.0)			
Network Port 1 (10/100/1000 Mbps Ethernet port, RJ-45) General	HDMI	1			
General	VGA	1			
	Network Port	1 (10/100/1000 Mbps Ethernet port, RJ-45)			
Power Supply DC12V, 4A	General				
	Power Supply	DC12V, 4A			

Power Consumption	Lower than 12 W
Net Weight	1.56 kg (3.44 lb)
Gross Weight	2.86 kg (6.31 lb)
Product Dimensions	1U, 375.0 mm × 289.0 mm × 53.0 mm (W × D × H) 14.76" × 11.38" × 2.09" (W × D × H)
Packaging Dimensions	433.0 mm × 141.0 mm × 366.0 mm (L × W × H) 17.05" × 5.55" × 14.41" (L× W × H)
Operating Temperature	-10 °C to +55 °C (+14 °F to +131 °F)
Operating Humidity	10%–90%
Installation	Desktop

Panels

